Amendments to the Claims:

This listing of claims replaces all prior versions and listings of claims in the application:

1. (Currently Amended) An organic light-emitting diode structure comprising:

first and second anodes;

first and second organic light-emitting layers disposed between the first and second anodes; and

a first common electrode disposed between the first and second organic light-emitting layers,

wherein the first organic light-emitting layer is for substantially emitting light in a first direction and the second organic light-emitting layer is for substantially emitting light in a second direction opposite to the first direction.

- 2. (Currently Amended) The organic light-emitting diode structure according to claim 1, wherein light is emitted from at least one of the first and second organic light-emitting layers when an electric current is passed between one of the first and the second anodes and the first common electrode.
- 3-4. (Canceled)
- 5. (Currently Amended) A display comprising:

organic light-emitting diode structures forming an array, each of the organic light-emitting diode structures comprising:

first and second anodes;

first and second anodes;

first and second organic light-emitting layers disposed between the first and the second anodes; and

a first common electrode disposed between the first and the second organic light-emitting layers,

wherein the first organic light-emitting layer is for substantially emitting light in a first direction and the second organic light-emitting layer is for substantially emitting light in a second direction opposite to the first direction.

- 6. (Previously Presented) The display according to claim 5, further comprising:
 - a first transistor coupled to each of the organic light-emitting diode structures; and
 - a second transistor coupled to each of the organic light-emitting diode structures.
- 7. (Original) The display according to claim 6, wherein the first transistor is coupled to one of the first and the second anodes of the organic light-emitting diode structures while the second transistor is coupled to the other one of the first and the second anodes of the organic light-emitting diode structures.
- 8. (Original) The display according to claim 6, further comprising a third transistor coupled to the first and the second transistors.
- 9. (Original) The display according to claim 6, wherein the first and the second transistors drive the organic light-emitting diode structures.

- 10. (Original) The display according to claim 8, wherein the third transistor switches the first and second transistors.
- 11. (Original) The display according to claim 5, wherein light is emitted from at least one of the first and the second organic light-emitting layers when an electric current passes between one of the first and the second anodes and the first electrode.

12-13. (Canceled)

- 14. (Currently Amended) A telecommunication device comprising:
 - a main body;
 - a flip-up door connected to the main body; and
 - a display beneath the flip-up door, the display comprising:

organic light-emitting diode structures forming an array, each of the organic light-emitting diode structures comprising:

first and second anodes;

first and second organic light-emitting layers disposed between the first and the second anodes; and

a first common electrode disposed between the first and second organic light-emitting layers,

wherein the first organic light-emitting layer is for substantially emitting light in a first direction and the second organic light-emitting layer is for substantially emitting light in a second direction opposite to the first direction.

15-16. (Canceled)

- 17. (Previously Amended) The telecommunication device according to claim 14, further comprising:
 - a first transistor coupled to each of the organic light-emitting diode structures; and
 - a second transistor coupled to each of the organic light-emitting diode structures.
- 18. (Original) The telecommunication device according to claim 17, further comprising a third transistor coupled to the first and the second transistors.